HS-422ST Accelerometer 4-20mA acceleration and temperature output via M12 Connector


Key Features


- 4-20mA acceleration output
- Temperature output
- Side entry for easy access



Building services, Pulp and Paper, Mining, Metals, Utilities, Automotive, Water, Pharmaceutical







Connection Details

Technical Performance Mechanical Mounted Base Resonance 10kHz min Case Material Stainless Steel **Acceleration Ranges** see: 'How To Order' table ±10% Sensing Element/Construction PZT/Shear Nominal 80Hz at 22°C Mounting Torque 8Nm 10Hz (600cpm) to 5kHz (300kcpm) ± 5% see: 'How To Order' table x 30mm long **Frequency Response** Mounting Bolt Provided - ISO10816 Weight 185gms (nominal) HS-AC010 - straight Isolation Base isolated Screened Cable Assembly Range see: 'How To Order' table HS-AC011 - right angle Mounting Threads 10mV/°C - 0-1V proportional to 0-100°C (to convert see: 'How To Order' table Temperature Output this to 4-20mA use the HS-540 module) Transverse Sensitivity Less than 5%


Electrical		Environmental	
Current Output	4-20mA DC proportional to acceleration	Operating Temperature Range	-25 to 90°C
Supply Voltage	15-30 Volts DC (for 4-20mA)	Sealing	IP67
Settling Time	1 second	Maximum Shock	5000g
Output Impedance	Loop Resistance 600 Ohms max. at 24 Volts	EMC	EN61326-1:2013
Case Isolation	>10 ⁸ Ohms at 500 Volts		

Typical Frequency Response												
Sensitivity Change %	50% 40% 20% -10% -10% -20% -30% -30% -50% 1			10		FI	100 requency	Hz		1,000		6,000

Applications

Fans, Motors, Pumps, Compressors, Centrifuges, Conveyors, Air Handlers, Gearboxes, Rolls, Dryers, Presses, Cooling, VAC, Spindles, Machine Tooling, Process Equipment

Vibration sensor should be firmly fixed to a flat surface (spot face surface may be needed to be produced and cable anchored to sensor body.)



How To Order

